
## Schottky Barrier Rectifiers



#### **Axial**



### **DO-201AD**



Dimensions: Inches (Millimetres)

#### Features:

- · High surge current capability.
- Void-free plastic in DO-201AD package.
- High current operation 3.0 Ampere at T<sub>L</sub> = 75°C
- Exceeds environmental standards of MIL-S-19500/228.

#### **Mechanical Data:**

Case : Moulded plastic DO-201AD.

Terminals : Axial leads, solderable per MIL-STD-202,

Method 208.

Polarity : Colour band denotes cathode.

Mounting Position : Any.

Weight : 0.04 Ounce, 1.1 Grams.

### **Maximum Ratings and Electrical Characteristics:**

At  $T_A$  = 25°C unless otherwise specified. Single phase, half wave, 60Hz, resistive or inductive load. All values except maximum RMS voltage are registered JEDEC parameters.

Parameter	SB350	SB360	Units	
Maximum recurrent peak reverse voltage	50	60		
Maximum RMS voltage	S voltage 35 42			
Maximum DC blocking voltage	50	60		
Maximum average forward rectified current at 75°C	3.	А		
Maximum overload surge current at 1 cycle	80			
Maximum forward voltage at 3.0 A dc	0.	V		
Maximum full load reverse current, full cycle average at 25°C	0.	mA dc		
Maximum DC reverse current at rated DC reverse voltage and 100°C	30		IIIA UC	
Typical junction capacitance (Note 1)	180		pF	
Typical thermal resistance (Note 2) RθJA	40	°C/W		
Operating and Storage temperature range	-50 to +125		°C	

#### Notes:

- 1. Measured at 1MHz and applied reverse voltage of 4.0V dc.
- 2. Thermal resistance junction to ambient.



Page 1 31/05/05 V1.0

# **Schottky Barrier Rectifiers**



### **Rating and Characteristics Curves**




Figure 1 - Forward Current Derating Curve




Figure 3 - Maximum Non-Repetitive Surge Current




Figure 2 - Typical Reverse Characteristics




Figure 4 - Typical Forward Characteristics



Page 2 31/05/05 V1.0

# **Schottky Barrier Rectifiers**






Figure 5 - Typical Junction Capacitance

### **Specifications**

V <sub>RRM</sub> maximum (V)	I <sub>F(av)</sub> maximum (A)	V <sub>F</sub> (V)	I <sub>FSM</sub> (A)	Length	Diameter	Part Number
50	- 3	0.75 at I <sub>F</sub> = 3A	80	9.5	5.3	SB350
60						SB360

Dimensions : Millimetres



## **Schottky Barrier Rectifiers**



Notes:

#### **International Sales Offices:**



AUSTRALIA - Farnell InOne Tel No: ++ 61 2 9645 8888

Fax No: ++ 61 2 9644 7898



FINLAND - Farnell InOne Tel No: ++ 358 9 560 7780

Fax No: ++ 358 9 345 5411



NETHERLANDS - Farnell InOne Tel No: ++ 31 30 241 7373

Fax No: ++ 31 30 241 7333



SWITZERLAND - Farnell InOne Tel No: ++ 41 1 204 64 64 Fax No: ++ 41 1 204 64 54

AUSTRIA - Farnell InOne

Tel No: ++ 43 662 2180 680 Fax No: ++ 43 662 2180 670



Tel No: ++ 33 474 68 99 99

Fax No: ++ 33 474 68 99 90



NEW ZEALAND - Farnell InOne

Tel No: ++ 64 9 357 0646 Fax No: ++ 64 9 357 0656



### UK - Farnell InOne

Tel No: ++ 44 8701 200 200 Fax No: ++ 44 8701 200 201



BELGIUM - Farnell InOne

Tel No: ++ 32 3 475 2810 Fax No: ++ 32 3 227 3648



#### GERMANY - Farnell InOne

Tel No: ++ 49 89 61 39 39 39 Fax No: ++ 49 89 613 59 01



#### NORWAY - Farnell InOne

Tel No: ++ 45 44 53 66 66 Fax No: ++ 45 44 53 66 02



#### UK - BuckHickman InOne

++ 44 8450 510 150 ++ 44 8450 510 130



BRAZIL - Farnell-Newark InOne Tel No: ++ 55 11 4066 9400

Fax No: ++ 55 11 4066 9410



### HONG KONG -

Tel No: ++ 852 2268 9888 Fax No: ++ 852 2268 9899



### PORTUGAL - Farnell InOne

Tel No: ++ 34 93 475 8804 Fax No: ++ 34 93 474 5288



#### UK-CPC ++ 44 8701 202 530

++ 44 8701 202 531



CHINA - Farnell-Newark InOne

Tel No: ++86 10 6238 5152 Fax No: ++86 10 6238 5022



#### IRELAND - Farnell InOne

Tel No: ++ 353 1 830 9277 Fax No: ++ 353 1 830 9016



Farnell-Newark InOne
Tel No: ++ 65 6788 0200

Fax No: ++ 65 6788 0300



### Tel No: ++ 44 8701 200 208



#### **DENMARK** – Farnell InOne

Tel No: ++ 45 44 53 66 44 Fax No: ++ 45 44 53 66 06



#### ITALY - Farnell InOne

Tel No: ++ 39 02 93 995 200 Fax No: ++ 39 02 93 995 300



#### SPAIN - Farnell InOne

Tel No: ++ 34 93 475 8805 Fax No: ++ 34 93 474 5107





#### ESTONIA - Farnell InOne

Tel No: ++ 358 9 560 7780 Fax No: ++ 358 9 345 5411



Tel No: ++ 60 3 7873 8000



#### SWEDEN - Farnell InOne

Tel No: ++ 46 8 730 50 00 Fax No: ++ 46 8 83 52 62

http://www.farnellinone.com

http://www.buckhickmaninone.com

http://www.cpc.co.uk

Disclaimer This data sheet and its contents (the "Information") belong to the Premier Farnell Group (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2004.



31/05/05 V1.0 Page 4